

<empty page to realign pages, flip-over to start worksheet Q1>

CSE 401 - LR Parsing Worksheet - Week 3

Problem 1

- a. Using the technique shown in lecture, construct the LR(0) state machine for this grammar. Remember to show the set of items that correspond to each state, including both any initial items and the resulting closure.

0. $S' ::= S \$$
1. $S ::= a Z$
2. $S ::= b$
3. $Z ::= a$
4. $Z ::= b S$

- state machine a number and use it to fill out one row of the table.

[illegible]

- need to keep track of the states. The initial state (s_1) has already been inserted onto the stack for you.

STACK	INPUT	ACTION
\$ 1	a b a b b \$	

Problem 2

- a. Using the technique shown in lecture, construct the LR(0) state machine for this grammar. Remember to show the set of items that correspond to each state, including both any initial items and the resulting closure.

- 0. $S' ::= S \$$
- 1. $S ::= a X a$
- 2. $S ::= b X$
- 3. $X ::= c$
- 4. $X ::= S c$

- [illegible]

- | STACK | INPUT | ACTION |
|-------|--------------|--------|
| \$ 1 | a b c c a \$ | |

Problem 3

- a. Using the technique shown in lecture, construct the LR(0) state machine for this grammar. Remember to show the set of items that correspond to each state, including both any initial items and the resulting closure.

0. $S' ::= S \$$
1. $S ::= (E)$
2. $E ::= E \&\& V$
3. $E ::= V$
4. $V ::= ! (E)$
5. $V ::= a$

- state machine a number and use it to fill out one row of the table.

STATE

- need to keep track of the states. The initial state (s_1) has already been inserted onto the stack for you.

STACK

\$ 1

INPUT

ACTION