

# CSE-571 Probabilistic Robotics

## Probabilistic Sensor Models

Beam-based  
Scan-based  
Landmarks

## Sensors for Mobile Robots


- **Contact sensors:** Bumpers
- **Internal sensors**
  - Accelerometers (spring-mounted masses)
  - Gyroscopes (spinning mass, laser light)
  - Compasses, inclinometers (earth magnetic field, gravity)
- **Proximity sensors**
  - Sonar (time of flight)
  - Radar (phase and frequency)
  - Laser range-finders (triangulation, tof, phase)
  - Infrared (intensity)
- **Visual sensors:** Cameras, depth cameras
- **Satellite-based sensors:** GPS

10/12/15

CSE-571 - Probabilistic Robotics

2

## Proximity Sensors



- The central task is to determine  $P(z|x)$ , i.e. the probability of a measurement  $z$  given that the robot is at position  $x$ .
- **Question:** Where do the probabilities come from?
- **Approach:** Let's try to explain a measurement.

10/12/15

CSE-571 - Probabilistic Robotics

3

## Beam-based Sensor Model

- Scan  $z$  consists of  $K$  measurements.
- $$z = \{z_1, z_2, \dots, z_K\}$$
- Individual measurements are independent given the robot position.


$$P(z | x, m) = \prod_{k=1}^K P(z_k | x, m)$$

10/12/15

CSE-571 - Probabilistic Robotics

4

## Beam-based Sensor Model



$$P(z | x, m) = \prod_{k=1}^K P(z_k | x, m)$$

10/12/15

CSE-571 - Probabilistic Robotics

5

## Proximity Measurement

- Measurement can be caused by ...
  - a known obstacle.
  - cross-talk.
  - an unexpected obstacle (people, furniture, ...).
  - missing all obstacles (total reflection, glass, ...).
- Noise is due to uncertainty ...
  - in measuring distance to known obstacle.
  - in position of known obstacles.
  - in position of additional obstacles.
  - whether obstacle is missed.


10/12/15

CSE-571 - Probabilistic Robotics

6


## Beam-based Proximity Model

Measurement noise



$$P_{hit}(z | x, m) = \eta \frac{1}{\sqrt{2\pi\sigma^2}} e^{-\frac{1}{2} \frac{(z - z_{exp})^2}{\sigma^2}}$$

Unexpected obstacles



$$P_{unexp}(z | x, m) = \eta \lambda e^{-\lambda z}$$


10/12/15

CSE-571 - Probabilistic Robotics

7


## Beam-based Proximity Model

Random measurement



$$P_{rand}(z | x, m) = \eta \frac{1}{z_{max}}$$

Max range




$$P_{max}(z | x, m) = \eta \frac{1}{z_{small}}$$

10/12/15

CSE-571 - Probabilistic Robotics

8

## Mixture Density



$$P(z | x, m) = \begin{pmatrix} \alpha_{\text{hit}} \\ \alpha_{\text{unexp}} \\ \alpha_{\text{max}} \\ \alpha_{\text{rand}} \end{pmatrix}^T \begin{pmatrix} P_{\text{hit}}(z | x, m) \\ P_{\text{unexp}}(z | x, m) \\ P_{\text{max}}(z | x, m) \\ P_{\text{rand}}(z | x, m) \end{pmatrix}$$

How can we determine the model parameters?

10/12/15

CSE-571 - Probabilistic Robotics

9

## Approximation

- Maximize log likelihood of the data
 
$$P(z | z_{\text{exp}})$$
- Search parameter space.
- EM to find mixture parameters
  - Assign measurements to densities.
  - Estimate densities using assignments.
  - Reassign measurements.


10/12/15

CSE-571 - Probabilistic Robotics


10

## Raw Sensor Data

Measured distances for expected distance of 300 cm.



Sonar




Laser

10/12/15

CSE-571 - Probabilistic Robotics

11

## Approximation Results




10/12/15

CSE-571 - Probabilistic Robotics

12

## Example




10/12/15

CSE-571 - Probabilistic Robotics

13

## Influence of Angle to Obstacle



10/12/15

CSE-571 - Probabilistic Robotics

14

## Summary Beam-based Model

- Assumes independence between beams.
  - Justification?
  - Overconfident!
- Models physical causes for measurements.
  - Mixture of densities for these causes.
- Implementation
  - Learn parameters based on real data.
  - Different models should be learned for different angles at which the sensor beam hits the obstacle.
  - Determine expected distances by ray-tracing.
  - Expected distances can be pre-processed.

10/12/15

CSE-571 - Probabilistic Robotics

15

## Scan-based Model

- Beam-based model is ...
  - not smooth for small obstacles and at edges.
  - not very efficient.

• **Idea:** Instead of following along the beam, just check the end point.

10/12/15

CSE-571 - Probabilistic Robotics

16

## Scan-based Model


- Probability is a mixture of ...
  - a Gaussian distribution with mean at **distance to closest obstacle**,
  - a uniform distribution for random measurements, and
  - a small uniform distribution for max range measurements.
- Again, independence between different components is assumed.

10/12/15


CSE-571 - Probabilistic Robotics

17

## Example



Map  $m$



Likelihood field

$$P(z|x,m)$$



10/12/15


CSE-571 - Probabilistic Robotics

18

## San Jose Tech Museum



Occupancy grid map



Likelihood field


10/12/15

CSE-571 - Probabilistic Robotics

19

## Scan Matching

- Extract likelihood field from scan and use it to match different scan.




10/12/15

CSE-571 - Probabilistic Robotics

20

## Scan Matching

- Extract likelihood field from first scan and use it to match second scan.



~0.01 sec

10/12/15

CSE-571 - Probabilistic Robotics

21

## Properties of Scan-based Model

- Highly efficient, uses 2D tables only.
- Smooth w.r.t. to small changes in robot position.
- Allows gradient descent, scan matching.
- Ignores physical properties of beams.
- Works for sonars?

10/12/15

CSE-571 - Probabilistic Robotics

22

## Additional Models of Proximity Sensors

- **Map matching (sonar, laser)**: generate small, local maps from sensor data and match local maps against global model.
- **Scan matching (laser)**: map is represented by scan endpoints, match scan into this map using ICP, correlation.
- **Features (sonar, laser, vision)**: Extract features such as doors, hallways from sensor data.

10/12/15

CSE-571 - Probabilistic Robotics

23

## Landmarks

- Active beacons (*e.g.* radio, GPS)
- Passive (*e.g.* visual, retro-reflective)
- Standard approach is **triangulation**
- Sensor provides
  - distance, or
  - bearing, or
  - distance and bearing.

10/12/15

CSE-571 - Probabilistic Robotics

24

## Distance and Bearing



10/12/15

CSE-571 - Probabilistic Robotics

25

## Probabilistic Model





1. Algorithm **landmark\_detection\_model**( $z, x, m$ ):  
 $z = \langle i, d, \alpha \rangle, x = \langle x, y, \theta \rangle$
2.  $\hat{d} = \sqrt{(m_x(i) - x)^2 + (m_y(i) - y)^2}$
3.  $\hat{\alpha} = \text{atan2}(m_y(i) - y, m_x(i) - x) - \theta$
4.  $p_{\text{det}} = \text{prob}(\hat{d} - d, \epsilon_d) \cdot \text{prob}(\hat{\alpha} - \alpha, \epsilon_\alpha)$
5. Return  $z_{\text{det}} P_{\text{det}} + z_{\text{fp}} P_{\text{uniform}}(z | x, m)$

10/12/15

CSE-571 - Probabilistic Robotics

26

## Distributions for $P(z|x)$



10/12/15

CSE-571 - Probabilistic Robotics

27

## Summary of Sensor Models

- Explicitly modeling uncertainty in sensing is key to robustness.
- In many cases, good models can be found by the following approach:
  1. Determine parametric model of noise free measurement.
  2. Analyze sources of noise.
  3. Add adequate noise to parameters (eventually mix in densities for noise).
  4. Learn (and verify) parameters by fitting model to data.
  5. Likelihood of measurement is given by "probabilistically comparing" the actual with the expected measurement.
- This holds for motion models as well.
- It is extremely important to be aware of the underlying assumptions!


10/12/15

CSE-571 - Probabilistic Robotics

28

[Ferris-Haehnel-Fox: RSS-06]

## GP-Based WiFi Sensor Model





10/12/15


CSE-571: Probabilistic Robotics

29

## GP-Based WiFi Sensor Model



Mean



Variance

10/12/15

CSE-571: Probabilistic Robotics

30